




LEGATE
Smart home

SMART POWER STRIP


Manual Guide



Legate Smart Plugs & Switches



Let's Get Started.



Install the app

Download the **Legate Smart Home** app from Google Play or the App Store on a compatible phone or tablet.



Register and login

Register on the app by using your contact number or Email address.




Connect to wifi

Make sure that your mobile phone and smart device are connected to 2.4 GHz wifi network.

*note: The distance between the phone and smart device should not be greater than 4meters while pairing both devices. If the signal is week you'll need a wifi booster. (Recommended Wifi Booster Version: **TP LINK TL-WA855RE**)


**Legate Smart Power Strip
to Legate Smart Home App**

Getting the Smart Device Ready



1


Plug the **Smart Power Strip** into a power outlet.



2


Press and hold the **ON/OFF Button** for 5s until the indicator light blinks.

Add Smart Device



3


Open Legate Smart Home app,
Click “+” or **Add Device**.



4


Under **“Electrical Engineering”** tab
Click **“Power Strip (Wi-Fi)”**.

Network Configuration



5


Click **“Confirm indicator rapidly blink”** button.



6


Enter your **Wifi Password**. Then click **“Confirm”** button.
(note: Only 2.4 GHz Wifi network are supported)

Network Configuration



7

Wait for the Smart Device connects to the app.




8

Click **“Done”** button when the Smart Device is successfully added.
(note: You can change the device’s name)


Legate Smart Power Strip Features

Main Function




On/Off Button

(note: You can change the switches' name and turn On or Off individually)




Set Countdown timer to automatically turn off the Smart Plug.



Add Schedule to automatically On or Off the Smart Plug.


Push Notification

Enable to turn off the notification.




1

Click **"Me"** button on Legate Smart Home app. Then click **"Settings"**.



2

Click **"Push Notification"** tab.




3

Can turn on or turn off the **"Enable notification"**


Remove Device from Legate Smart Home app

The device will restore to default settings.




1

Click "... " button on upper right corner of Smart Power Strip's main page.



2

Click **"Remove Device"** tab.




3

Click **"Confirm"** button to completely remove the device from the Legate Smart Home app.

Legate Smart Power Strip Configuration & Specifications

Product Configuration



Reset:

Press and hold the **ON/OFF Button** for 5 seconds until the Light Indicator blinks. Then the device will be automatically removed to the Legate Smart Home app.

Specifications

Product Model	:	SA-P302B
Rated Voltage	:	AC100V - 240V
Rated Current	:	50 / 60Hz
Usb Output	:	10A
Power Cable	:	5V/2.1A
Ouput Port	:	3USB
Wireless Type	:	2.4GHz 802.11b / g / n wireless network
Free app	:	Legate Smart Home
Support systems	:	IOS 7.0 or above, Android 4.0 or above
Voice Control	:	Google Home



LEGATE[®]
Smart home

Your one stop shop for all your Smart Home needs

www.legate.com.sg